

CONTROL TRANSFORMER


Primary 0 - 220 - 230 - 240 U
0 - 380 - 400 - 415 N

Secondary Options 0 - 12 J
0 - 24 B
0 - 48 E
0 - 110 F
0 - 230 U

Primary and secondary terminals are on opposite sides to each other for 25 - 50va
Primary and secondary terminals are on the same side as the earth terminal for 100 - 2500va

VA	A	B	C	D	E	kg
25	66	68	77	50	40	0.7
50	75	70	86	53	47	1.1
75	75	76	86	53	53	1.5
100	84	78	95	60	68	2.1
150	96	76	102	68	63	2.25
200	96	86	102	68	73	2.8
250	96	101	102	68	88	3.7
300	120	88	122	80	68	4.4
400	120	100	122	80	81	5.3
500	120	120	122	80	103	6.5
750	150	145	140	105	80	8.0
1000	150	161	140	105	96	10.0
1500	150	188	140	105	123	14.0
2000	192	150	165	153	125	20.5
2500	192	178	180	153	153	24.0

ALL DIMENSIONS IN mm

REV.	DATE	DESCRIPTION	BY	CHK	APP	VENDOR NAME		TITLE			
00		ISSUED FOR REVIEW	PB	MB	MB	BOARDMAN TRANSFORMERS LTD		CONTROL PANEL TRANSFORMER - CL			
						VENDOR NO.		MULTIPLE TAPPED INPUT			
						DRAWING NO.		OUTPUT OPTIONS			
						SCALE		Manufactured to comply with the requirements of BS171 IEC61558			
						SIZE	CAGE CODE	DWG NO	REV		
						A4			00		
									SHEET	OF	REV.
									1	1	00